

DLZ CREATOR

Adaptive Digital Mixer For Podcasting and Streaming, Featuring Mix Agent™ Technology

Overview Channel FX	pshots Samples Pshots Samples Particular Partic	-13.5dB 12 -28.2dB -12.6dB -12.6dB	R
			2)



DLZ CREATOR

DLZ CREATOR

Adaptive Digital Mixer For Podcasting and Streaming, Featuring Mix Agent™ Technology

Better. Faster. Creator.

DLZ Creator is an adaptive digital mixer that enables creators of all levels to quickly get pro results for podcasts, YouTube, and live streaming.

DLZ Creator is designed to make you a better content producer. Mix Agent[™] is your personal audio assistant that guides you through setup, including setting your gain levels.

AutoMix manages levels for up to 4 mics, so everyone can always be heard. Using Mix Minus with your Bluetooth[®]-connected smartphone brings a caller into your mix with no audible echo.

The flexible design includes recording/streaming to computer, SD card, or USB flash drive.

FEATURES:

- Get pro results at any experience level
- Mix Agent[™] assists in setup and more
- AutoMix manages levels for up to 4 voices
- Connect call-in guests via Bluetooth
- Record/stream to computer, flash drive or SD card
- 4 Onyx80 mic preamps
- 10.1" touchscreen

APPLICATIONS:

Podcasting, broadcasting, live streaming, and many, many more.





DLZ CREATOR SPECIFICATIONS

General Digital

Sample Rate:	48 kHz
A/D/A Bit Depth:	24-bit
System Latency:	~3 ms
Equivalent Noise:	-143.4 dBV (A-weighted]

Inputs	
Inputs:	4x balanced/unbalanced combo jacks, 1/4″ balanced/unbalanced stereo jack, 1/8″ stereo jack
XLR Mic Pre:	Onyx 80 mic preamps
Input Impedances:	4 k Ω balanced (microphone), 10 k Ω balanced (instrument), 5 k Ω unbalanced (instrument)

Outputs

Outputs:	Balanced/unbalanced 1/4" main out jacks, 4x stereo headphone jacks
Line Output Maximum Level:	14 dBu
Headphone Output Power:	30 mW

Bluetooth • U	SB • SD
Bluetooth:	5.0
USB:	Format: USB 2.0 HS (480Mb/s)
SD:	Multitrack (12 chan + main mix) / 24-bit / 48kHz SD speed class 10 or speed class UHS recommended

Recording / Networking	
Recording Storage:	microSDHC, microSDXC, USB-A removable drive (FAT32 – minimum 100MB/s)
Data Transfer:	Integrated SD 3.0 104 MB/s
Network Connectivity:	Ethernet 10/100

Power Requirements

Line Input Power:	18V===1.5A

Physical Properties (product)

Height:	4.1 in / 103 mm
Width:	13.0 in / 330 mm
Depth:	15.0 in / 381 mm
Weight:	6.1 lb / 2.8 kg

Physical Properties (packaged product)

Height:	8.5 in / 216 mm
Width:	15.2 in / 386 mm
Depth:	15.7 in / 399 mm
Weight:	10.9 lb / 4.9 kg

Options

DLZ Creator Backpack	P/N 2056135
----------------------	-------------

Ordering Information

P/N 2053754-00 (US)
P/N 2053754-01 (EU)
P/N 2053754-02 (JP)
P/N 2053754-03 (UK)
P/N 2053754-04 (AU)
P/N 22053754-05 (CN)
P/N 2053754-06 (BZ ~120V)
P/N 2053754-07 (AR)
P/N 2053754-08 (KR)



DLZ CREATOR

DLZ CREATOR DIMENSIONS







DLZ CREATOR REAR PANEL



Electronic files for this product are available at: www.mackie.com

Specification Sheet	DLZ CREATOR SS.PDF
Owner's Manual	DLZ CREATOR OM.PDF

LOUD Audio, LLC. is always striving to improve our products by incorporating new and improved materials, components, and manufacturing methods. Therefore, we reserve the right to change these specifications at any time without notice.

"Mackie" and the "Running Man" figure are registered trademarks of LOUD Audio, LLC. All other brands mentioned are trademarks or registered trademarks of their respective holders, and are hereby acknowledged.

©2023 LOUD Audio, LLC. All rights reserved.





www.mackie.com 19820 North Creek Parkway #201 Bothell, WA 98011 USA 800-898-3211, Fax 425-487-4337

Part No. SW1368 Rev. A 05/23